

IP Softphone Edition of PC Phone Software

Quick Reference Guide

for IP Softphone

Model No. KX-TDA0350

Thank you for purchasing the Panasonic PC Phone Software, KX-TDA0350.

Please read this manual before using this product and save for future use.

This manual is designed to provide instructions for installing the IP Softphone software on your personal computer.

Table of Contents

System Requirements.....	1
Introduction.....	2
Conditions.....	2
Installing the IP Softphone Software.....	3
Uninstalling the IP Softphone Software.....	5
Starting and Registering the IP Softphone Software.....	5
Upgrading the IP Softphone Software.....	10
Features List.....	12

System Requirements

- Microsoft® Windows® XP Professional SP2
- Minimum Requirements (for installing the IP Softphone only)
 - CPU: Pentium® M 1.86 GHz
 - RAM: 512 MB
 - HDD: 50 MB available space (when installing)
 - Display: XGA (1024 x 768)
 - LAN (Ethernet): 100BASE-T
 - Peripheral Devices: Sound Board, Speaker, Microphone, CD-ROM drive
- PBX: Main Processing (MPR) software version of the Hybrid IP-PBX must be as follows:
 - KX-TDA100/KX-TDA200: PMPR Software File Version 3.0000 or later
 - KX-TDA600: PLMPR Software File Version 3.1000 or later
- IP-EXT card: Local Processor (LPR) software version of the IP-EXT card installed in the PBX must be as follows:
 - PIPEXT Software Version 1.001 or later
 - PVOIPEX Software Version 1.011 or later
- Network Settings: Network VoIP specifications must be as follows:
 - CODEC: G.711 (G.729 is not supported.)
 - RTP sampling rate: 20 ms

Trademarks

- Microsoft and Windows are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries.
- Pentium is a trademark or a registered trademark of Intel Corporation or its subsidiaries in the United States and other countries.
- All other trademarks identified herein are the property of their respective owners.
- Screen shots reprinted with permission from Microsoft Corporation.

Introduction

The IP Softphone is designed to interwork with a Panasonic Hybrid-IP PBX (KX-TDA series), and enables the personal computer to handle calls instead of the proprietary telephone.

Conditions

- In some cases, clear communication may not be possible, due to network conditions and the specifications of the PC and headset. Confirm that CO line and intercom calls can be completed successfully using the IP Softphone's Trial Mode before registering a license. A registered license cannot be used at another PC.
- The feature specifications of the IP Softphone are basically the same as those for the KX-NT136 IP proprietary telephone. For installation and operation instructions, refer to the documentation for the KX-NT136.
The feature differences from KX-NT136 are as follows:
 - Programmable melodies and ring tones are not available.
 - Automatic Redial is available only for ISDN lines.
- To install the IP Softphone on, or to uninstall it from a PC running Windows XP Professional SP2, you should be in the group "Administrators". The user in any other groups is not authorized.
- If audio becomes increasingly delayed the longer you use IP Softphone, there may be a problem with the PC's audio driver. In this case, install another compatible audio driver (not another version of the same driver).
- If using Windows Firewall, you may not hear a dial tone when clicking the SP-PHONE button. In this case, select the "software_ippt" check box in the exceptions list for Windows Firewall.
- The Automatic Pop-up feature does not operate in situations such as the following:
 - When a call is answered automatically
 - When using Live Call Screening in hands-free mode
- Specifications are subject to change without notice.
- The design of the final software may differ slightly from the screenshots shown in this manual.

Installing the IP Softphone Software


Notice:

Shut down any other applications before installing the software.

1. Double-click "Setup.exe" on the CD-ROM.




2. Click Next.



3. Read the License Agreement carefully.

Installing the IP Softphone Software

4. If you accept the terms of the License Agreement, select I accept the terms in the License Agreement, and then click Next.



5. Click Browse to change the installation folder. This step is optional, and can be skipped.
6. Click Install.



7. Click Finish.

Uninstalling the IP Softphone Software


Uninstall the software from [Control Panel] -> [Add/Remove Programs].

Starting and Registering the IP Softphone Software

1. Start IP Softphone.

Notice:

Without the Registration Key, the IP Softphone can be used for only 60 days from the date of installation.



2. Click Register Now.

Notes:

- If you click Yes, all features (both basic and optional) of the IP Softphone will be available for 60 days from the date of installation if no license is registered.
- If you click No, the software will close.

Starting and Registering the IP Softphone Software

KX-TDA0350 License Registration

Basic Features

Two licenses are required for basic features.

1st License

Registration Number 0350 - 2010 - 2220 - 0977

Registration Key - - - Register

2nd License

Registration Number 1350 - 2020 - 2220 - 0977

Registration Key - - - Register

Optional Features

3rd License : Dial Paste feature

Registration Number 2350 - 2030 - 2220 - 0977

Registration Key - - - Register

4th License : Recording feature

Registration Number 3350 - 2040 - 2220 - 0977

Registration Key - - - Register


OK

3. Enter the Registration Key for 1st License, and click Register.
4. Enter the Registration Key for 2nd License, and click Register.
5. Click OK, and then Yes.

Notes:

- The 1st and 2nd licenses are required for basic features. To use optional features, additional licenses are required as follows:
 - Dial paste feature: 3rd license required
 - Call recording feature: 4th license requiredThese licenses can be registered at any time after registering the basic licenses, by accessing this screen.
- If you register only the 1st and 2nd licenses, the optional features will become unavailable even if less than 60 days from the date of installation.

Starting and Registering the IP Softphone Software



6. Select the network adaptor to use.
7. Enter the IP address of the IP-EXT card installed in the PBX.
8. Click OK.

Note:

Before you click OK, confirm that the port of the IP-EXT card in the PBX is in registration mode (i.e., waiting for a response from the IP Softphone). For more details, refer to **Information about IP Proprietary Telephones** for the KX-TDA series PBXs.

Starting and Registering the IP Softphone Software



9. Confirm that calls can be made from the IP Softphone by clicking the handset and dialing.

Starting and Registering the IP Softphone Software



10. To end the call, click the hookswitch.

Upgrading the IP Softphone Software

Note


This operation is required only for upgrading from the version 1.056 IP Softphone software.

To upgrade from version 1.1 or later, just install the new version. You do not need to re-register your Registration Keys.

1. Start the current version of IP Softphone, and then click OPTIONS.



2. Click Configuration.



Upgrading the IP Softphone Software

3. Click the License & Software Version tab, and then click Registration Menu.

KX-TDA0350 License Registration

Basic Features

Two licenses are required for basic features.

1st License

Registration Number: 7350 - 2010 - 8000 - 0008

Registration Key: 4523 - 0614 - 6078 - 0786 Register

2nd License

Registration Number: 8350 - 2020 - 8000 - 0008

Registration Key: 7160 - 2002 - 6078 - 0786 Register

Optional Features

3rd License: Dial Paste feature

Registration Number: 9350 - 2030 - 8000 - 0008

Registration Key: 5560 - 2006 - 6078 - 0786 Register

4th License: Reserved

Registration Number: 0350 - 2040 - 8000 - 0008

Registration Key: - - - Register

OK

4. Take note of the Registration Keys for your licenses so that you can enter the same Registration Keys for the new version of IP Softphone.

5. Click OK, and then click Cancel.



6. Click the close button.

7. Install the new version of IP Softphone.

For the installation procedure, refer to **Installing IP Softphone Software** in this guide.

Features List

Outside (CO) Line button
 Off-hook
 On-hook
 Feature number
 Talk
 Direct Station Selection button
 Confirmation Tone
 Ringback Tone
 C. Tone R.B. Tone

Feature	Operation
Making Calls	
Calling	To an extension ▶ extension no. ▶
	To an outside party ▶ ▶ outside phone no. ▶
Redial	▶ REDIAL ▶
Quick Dialing	▶ quick dial no. ▶
One-touch Dialing	To store ▶ ▶ 2 ▶ desired no. (max. 32 digits) ▶ ▶
	To dial ▶ — assigned as a One-touch Dialing button ▶
Operator Call	▶ 0 ▶
Personal Speed Dialing	To store ▶ * 3 0 ▶ personal speed dial no. (2 digits) ▶ desired no.*1 (max. 32 digits) ▶ #
	To dial ▶ ▶ * ▶ personal speed dial no. (2 digits) ▶
System Speed Dialing	To dial ▶ ▶ system speed dial no. (3 digits) ▶
Doorphone Call	▶ * 3 1 ▶ doorphone no. (2 digits)
Automatic Callback Busy	To set <i>While hearing a busy tone</i> 6
	To cancel ▶ * 4 6
	To answer from an idle extension <i>While hearing a callback ring</i>
	To answer from an idle outside line <i>While hearing a callback ring</i> ▶ outside phone no. ▶
During a Conversation	
Call Hold	To hold
	To retrieve a call at the holding extension ▶ / ▶
	To retrieve an outside call from another extension ▶ ▶
Call Transfer	extension no. To an extension outside phone no. To an outside party

*1 Enter outside line access number before outside phone number.

Features List

Feature	Operation									
Useful Features										
Call Park	To set <i>During a conversation</i> C. Tone * 5 2 ► <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td style="text-align: center;">parking zone no. (2 digits)</td><td style="text-align: center;">Specified</td></tr><tr><td style="text-align: center;">*</td><td style="text-align: center;">Auto</td></tr></table>		parking zone no. (2 digits)	Specified	*	Auto				
	parking zone no. (2 digits)	Specified								
*	Auto									
To retrieve ► * 5 2 ► <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td style="text-align: center;">stored parking zone no. (2 digits)</td></tr></table>		stored parking zone no. (2 digits)								
stored parking zone no. (2 digits)										
Multiple Party Conversation	To add other parties during a conversation C. Tone <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td style="text-align: center;">desired phone no.</td></tr></table> ► ► C. Tone Talk to the new party.		desired phone no.							
	desired phone no.									
To leave a conference C. Tone Talk with multiple parties.										
Call Pickup	► <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td style="text-align: center;">(DSS)</td></tr><tr><td style="text-align: center;">* 4 1</td></tr><tr><td style="text-align: center;">* 4 0</td></tr></table> ► <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td style="text-align: center;">extension no.</td><td style="text-align: center;">Directed</td></tr><tr><td style="text-align: center;">group no. (2 digits)</td><td style="text-align: center;">Group</td></tr></table> ►		(DSS)	* 4 1	* 4 0	extension no.	Directed	group no. (2 digits)	Group	
(DSS)										
* 4 1										
* 4 0										
extension no.	Directed									
group no. (2 digits)	Group									
Sending a Call Waiting Tone	<i>While hearing a busy tone</i> 1 ► Wait for an answer. ►									
Paging	To page ► * 3 3 ► <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td style="text-align: center;">paging group no. (2 digits)</td></tr></table> Announce. Wait for an answer.		paging group no. (2 digits)							
	paging group no. (2 digits)									
	To answer ► * 4 3									
To allow/deny a paged announcement ► <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td style="text-align: center;">* 7 2 1 1</td><td style="text-align: center;">Deny</td></tr><tr><td style="text-align: center;">* 7 2 1 0</td><td style="text-align: center;">Allow</td></tr></table>		* 7 2 1 1	Deny	* 7 2 1 0	Allow					
* 7 2 1 1	Deny									
* 7 2 1 0	Allow									
Message Waiting	Caller	To leave a message waiting indication <i>When the called extension is busy or does not answer</i> 								
	Called extension	To call back ► ►								
Log-in/Log-out	► <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td style="text-align: center;">* 7 3 6 1</td><td style="text-align: center;">For Log-in</td></tr><tr><td style="text-align: center;">* 7 3 6 0</td><td style="text-align: center;">For Log-out</td></tr></table> ► <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td style="text-align: center;">ICD Group extension no.</td><td style="text-align: center;">Specified</td></tr><tr><td style="text-align: center;">*</td><td style="text-align: center;">All</td></tr></table>		* 7 3 6 1	For Log-in	* 7 3 6 0	For Log-out	ICD Group extension no.	Specified	*	All
* 7 3 6 1	For Log-in									
* 7 3 6 0	For Log-out									
ICD Group extension no.	Specified									
*	All									

**Panasonic Consumer Electronics Company,
Division of Panasonic Corporation of North America**
One Panasonic Way, Secaucus, New Jersey 07094

Panasonic Puerto Rico, Inc.
San Gabriel Industrial Park, Ave. 65 de Infantería, Km. 9.5,
Carolina, Puerto Rico 00985

<http://www.panasonic.com/csd>

Copyright:

This material is copyrighted by Panasonic Communications Co., Ltd., and may be reproduced for internal use only. All other reproduction, in whole or in part, is prohibited without the written consent of Panasonic Communications Co., Ltd.

© 2006 Panasonic Communications Co., Ltd. All Rights Reserved.

PSQX4145YA KK0306TM1076